

SPOOLORGANIZER/400™ UPDATE INSTRUCTIONS

New Release: Release 05, Modification 07, PTF 1801

System Requirements:

AS/400: OS/400 Version 6 Release 1 Modification 0 or later.
Security level 40 or less

SpoolOrganizer/400™: Release 4.0 PTF 0000 or later.

Enhancements

Release 5.7 PTF 0000

ASP Support added. Spool Organizer product libraries can be installed in ASPs other than the System ASP (ASP = 1). Basic ASPs (1 – 32) and Independent ASPs (33 – 256) are supported.

Multiple Instances per LPAR supported. Spool Organizer can have multiple instances within the same LPAR. Each instance operates independently of the others. Multiple instances can be running at the same time.

Release 5.6 PTF 1203

Online Database Mass Change functions added. Mass changes can be made to the Online Database. For example the administrator can change the Type and Period to ND – 30 to a large number of entries. Two methods can be used:

- **CHGSOENT command.** Allows the administrator to specify a search spec and the fields to change.
- **BSOMCOLE API.** Allows a HLL developer to write a simple program to change entries in the Online Database.

MGROPTE command. The MGROPTE (Migrate Optical Entries) command now has the RMVOPT (remove optical entries) parameter, which provides the option to remove migrated entries from the Optical Catalog.

DIRSPLE and DIROUTQ commands. The DIRSPLE and DIROUTQ commands now have the CMBOVPRT (combine overprint lines) option, which allow the option to place all print records with the same line number into the same print record.

Release 5.6 PTF 0000

Spool PDF Overlay/400™ interface added. Generated PDF files can be created by the Spool PDF

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

Overlay/400™ product, which supports the following:

- Overlays
- Images
- Multiple, Embedded Fonts

All Spool Organizer functions that create PDF files will support the Spool PDF Overlay/400 interface. Contact BDS for a 30-day free trial of the Spool PDF Overlay/400 product.

Release 5.5 PTF 0601

Optical Migration Aid added. Spool entries archived to an Optical Library can be migrated to tape (or ARCFILE) or to the Online Database. Corresponding Optical Catalog entries can be migrated. Index entries pointing to optical entries will be migrated.

Release 5.5 PTF 0000

Encryption added. E-mail attachments and IFS files can be encrypted. The industry standard Rijndael algorithm with a 128 bit key is supported. The encrypted file is Windows exe file that users execute. Users must enter a password to access the attachment. All Spool Organizer functions that support E-mail support encryption.

Tape support enhanced. A tailoring option was added, allowing the installation to skip tape mount messages when spool entries are printed from tape.

Problems Corrected

<u>REL</u>	<u>PTF</u>	<u>DESCRIPTION</u>
5.7	1801	Email PDF, prev. email attempt abends, larger PDF work file causes corrupt PDF attachment file.
5.7	1801	Work file create, size allocations changed to (10000 10000 10000).
5.7	1801	Install & Update, Check for user QSECOFR before setting Storage Area to *NONE.
5.7	1801	Report IFS Close errors.
5.6	1701	Email, email addresses passed to IBM API no longer upper-case translated.
5.6	1505	Tasks receive CPD0193 Not authorized to pgm QPMLPMGT.
5.6	1504	Dtaq's BSOBDMGR, BSODXMGR, BSOLOGREQ, make max size 2 giga-byte.
5.6	1504	Temp work sple file name, use 7-digit number.
5.6	1504	Monitor to Bundle Manager communication, compress certain data.
5.6	1503	(Enhancement) Bundle Manager, partial print, performance greatly enhanced.
5.6	1503	(Enhancement) Attribute Change Specs, added EXPDATE and DAYS parameters.
5.6	1503	PDF, > 200k pages cause MCH0603 in BSO285 @ stmt 390.
5.6	1503	(Enhancement) PDF, support file sizes up to 10 giga-bytes.
5.6	1502	Internal modifications.
5.6	1501	BDS User Profile Coordinator, MCH0603 in BDS01 at statement 166.

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

- 5.6 1401 V7R1 & V6R1 IBM cumulative PTF causes MCH0601 in QC2POSIX, BSO262.
- 5.6 1401 Bundles, Partial Prt type R (range), eml PDF causes MCH1202 in BSO139 @ 3618.
- 5.6 1302 EMLSPLE cmd, distribution list address invalid, loop sending msg SPO1175.
- 5.6 1302 Monitors, do not send SPO1167 (Invalid Job date/time). Use Sple open date/time.
- 5.6 1302 DIRSPLE & DIROUTQ cmds, not able to enter type *TSV.
- 5.6 1302 List displays, >9999 entries causes I-O error.
- 5.6 1301 (Enhancement) Monitors, no limit to the number of Selection Specs and Bundle Specs that can be loaded.
- 5.6 1301 (Enhancement) Mirroring, replicated system's password can be specified on the production machine.
- 5.6 1204 (Enhancement) DIRSPLE & DIROUTQ cmds, added *DFT to CMBOVPRT parm.
- 5.6 1203 MGROPT command, I-O error (duplicate key) in pgm BSO345 for file BSOWNT.
- 5.6 1202 V7R1, Optical Functions, MCH1202 in BSO192 at 245.
- 5.6 1202 Bundle Manager, Dup Key in file BSOBSTX causes IO error in BSO125 @ 3261.
- 5.6 1201 Monitors or DSPOLE, email sple, TSV, MCH3601 received in BSO286 @ 161.
- 5.6 1104 Create CSV IFS file, create headings gives MCH1202 in BSO286 @ 169.
- 5.6 1103 DSPOLE exit pgm, spool file attributes parm spaces.
- 5.6 1103 Sample source BSOIX1, SPLFA0200 parm size increased to 15360 chars.
- 5.6 1103 Create IFS from optical spool entry, report errors w/more specific message.
- 5.6 1102 Display a sple, delete work prtf objs in QTEMP after use.
- 5.6 1102 (Enhancement) DSPOLE cmd, added opt to write selected sple's to the IFS.
- 5.6 1101 ARCOUQT, OPTOUTQ, DIROUTQ, FCHOUTQ cmds, sple deleted causes SPO1051 and cmd to terminate.
- 5.6 1101 (Enhancement) PDF, added compress page data option.
- 5.6 1101 Update, MCH3601 in BSOUP12 possible.
- 5.6 1101 Function checks, I-O errors due to record lock timeouts.
- 5.6 1003 DIRSPLE, DIROUTQ cmds, Invalid PDF Spec, MCH3401 @ 867 or 970.
- 5.6 1002 Text, CSV, TSV, HTML, Combine overprinted lines.
- 5.6 1001 Install/Update, V5R4 machines, CPF3773 (xxx objects not restored).
- 5.6 0000 PDF files, inch to cm multiplier incorrect.
- 5.5 0904 DSPOLE, list, 6=Prt, F4, Read-only Auth gives not authorized error.
- 5.5 0904 Manage Bundle Entries Partial Print, invalid data accepted if F6 pressed.
- 5.5 0903 Email, date fmt different (job & sysval), fcn chk in BSO295 @ 4400
- 5.5 0903 Monitors, Email, sple deleted gives API err, MCH3401 in BSO005.
- 5.5 0903 Monitors, Indexing (Dissassemble), file BSOOLD remains open when Monitor idle.
- 5.5 0903 Monitor startup, cannot allocate data area BSO40, pgm BSO013 @ 9300.
- 5.5 0902 (Enhancement) xxxOUTQ cmds, no limit on number of entries in outq.
- 5.5 0902 Indexing (Dissassemble), zero prt recs in sple causes MCH3401, damaged entry msg.
- 5.5 0902 Email, long MSF delays and > 1000 sends per job, wrong msg contents sent.
- 5.5 0902 Spool File Attr Output Priority not numeric causes MCH1202.
- 5.5 0901 Search ops, Rel='CT', 'Name' fields => may get "invalid characters" msg.
- 5.5 0804 Use latest version (1.2.3) of Flate compression utility
- 5.5 0803 Display a spool entry, F15 to email, type CSV gives MCH0603 in BSO262 @ 1322.
- 5.5 0803 (Enhancement) Email, type PDF, use Flate to compress page data.
- 5.5 0802 Add Processor Group to password expiration messages.

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

- 5.5 0801 ARCARCFTDA cmd, many DupKey messages in the joblog.
- 5.5 0801 E-mail a Bundle, no entries in Bundle causes function check in BSO262
- 5.5 0801 Manager DataQ's (Bundle, Index, Log), make size 2 gigabyte
- 5.5 0704 E-mail, Addr USRPRF(xxx), SMPT route specified in WRKDIRE screen gives CPF3C17, SPO1170
- 5.5 0704 MGROPT cmd, LAN-attached, gives OPT6704 (OPNDR cmd not supported)
- 5.5 0704 (Enhancement) Added MGRCATE (Migrate Archive Catalog Entries) command.
- 5.5 0703 E-mail, MIME-Version keyword, wrap parentheses around comment.
- 5.5 0703 E-mail, non-PDF attachments, do not generate mult lines per print line.
- 5.5 0703 DIROUTQ, DIRSPLE cmds, do not generate mult lines per print line.
- 5.5 0702 PRTOLE cmd, I/O op failed, stmt 407 status 42.
- 5.5 0701 DSPOLE cmd, opt 6 to Print, sple not on media causes submitted job to loop.
- 5.5 0701 FORMFEED(*CONT2) can cause fcn chk in BSO008 at 21600.
- 5.5 0701 ARCOLE, OPTOLE cmds, many DUPKEY messages may appear in joblog.
- 5.5 0701 (Enhancement) All physical and logical files now ACCPTHSIZ(*MAX1TB).
- 5.5 0605 E-mail addresses, allow hyphen in 1st character.
- 5.5 0604 Display a spool entry, *AFPDS, MCH0601 received in BSO052 @ 3869.
- 5.5 0604 Display a spool entry, *AFPDS, 1 print line taking multiple records optimized.
- 5.5 0604 Monitors, Attribute Change spec, sple deleted causes fcn-chk.
- 5.5 0604 Tailoring Options Display, E-mail Options, Page Measurement *SPLFILE not valid.
- 5.5 0604 Display a Spool Entry, F-15 to E-mail, *PDF, E-mail spec's Page Measurement attr different than PDF spec's causes generated PDF unreadable.
- 5.5 0603 Bundle Manager, Large Bundles, SPO1088 & SPO1086 received, entries not added.
- 5.5 0603 Index Mgr, test End cmd's timestamp before honoring.
- 5.5 0603 Define Bundle Desc, Disp Specifications, From/To not *ALL shows no entries.
- 5.5 0603 DSPSOLOG, search screen, added Bundle Seq and Linum fields.
- 5.5 0603 Monitor, AttrChg HOLD-YES & ToOutq-HOLD gives CPF3337, Monitor ends.
- 5.5 0603 Data Queues now use the Auto Reclaim attribute.
- 5.5 0602 CSV/TSV Specs, from/to columns and lines, allow up to 512.
- 5.5 0000 DSPOLE.htm, Optical Entries, Dis-assembled gives MCH1202 in BSO091.
- 5.5 0000 DSPOLE.htm & WRKACTBDL.htm, CSV, Display gives only a Save option, no Open option.
- 5.5 0000 Disp Sple, E-mail (F-15), invalid E-mail spec causes wrong field highlighted.
- 5.5 0000 Define E-mail specs, attachment name truncate size truncates specified name.
- 5.5 0000 Define E-mail specs, increase truncate size default to 10.
- 5.5 0000 Define E-mail specs, mass change, edit error causes display to hang.
- 5.5 0000 E-mail, attachment name > 32 characters truncated.
- 5.5 0000 SAVOUTQ cmd, outq or lib *ALL or *LIBL, outq or lib not found, send warning msg instead of error.

Installation Instructions

Before you begin:

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

1. The update will overlay any changes made to **BDS** objects by the user (i.e. BDS subsystem description). The user must reapply any changes made to **BDS** supplied objects after applying the update.
2. The update will rename/delete/restore user data files. If for any reason the update process does not complete normally, or receives a function check, Spool Organizer will be unusable and/or user data will be lost. Therefore, we recommend you back up the libraries **BRODERICK**, **BDSDATA**, **BDSBASE** (if it exists) and the IFS directory **/BRODERICK** before starting the update.
3. The supplied media contains the entire Spool Organizer package. If you are installing a new instance of Spool Organizer, follow the instructions in Chapter 2, "Installation". Otherwise, use the instructions below to update your existing Spool Organizer instance to the new release.
4. If your old release is prior to 5.5 0701, the update will copy/reformat many files, some may be large. This may take a long time and will require temporary disk space approaching twice the size of Library **BDSDATA**. A quick time estimate for the copy/reformat processing is 2 times the amount of time that a RSTLIB would take for library **BDSDATA**, or 4 times the amount of time that a SAVLIB would take for library **BDSDATA**.
5. If your old release of Spool Organizer is prior to 5.7 0000, this update will create a new library **BDSBASE** and will move subsystem, class, job description, job queue, and some shared-product objects from library **BRODERICK** to **BDSBASE**. You should update your HA/DR procedures to process library **BDSBASE** similar to how you process library **BRODERICK**.
6. If you have multiple instances of Spool Organizer running on this LPAR, or you already have one of our other products running on this LPAR you may also need to update them before giving users access to them. Refer to Appendix L, Release Compatibility in the Spool Organizer Users Guide for more information. Failure to do so could cause other BDS software to stop working after this instance is updated.
7. These update procedures update a single instance of Spool Organizer. If you have multiple instances of Spool Organizer running in this LPAR, you must run this procedure for each instance.

Update Procedure:

1. **Important:** Sign on as the security officer (QSECOFR).
2. Stop all Monitors and Subsystem BDS. Stop all other instances of Spool Organizer and all other BDS products running on this LPAR.
3. Determine your current release of Spool Organizer. Enter the following command:

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

BRODERICK/BSOSETUP

Write down somewhere the Release, Modification, and PTF displayed.

For example, 05 06 1102 is 5.6 1102. If your release is prior to 4.0 0000 you cannot use these instructions. See “Prerequisites” on Page 1 for more information.

4. Install media. Load the install programs from the BDS supplied media. Enter one of the following:

If you are using Tape:

```
RSTOBJ OBJ(BSOUP*) SAVLIB(SPOR40) DEV(XXXXX)VOL(*MOUNTED) RSTLIB(QTEMP)
```

If you are using CD-ROM:

```
RSTOBJ OBJ(BSOUP*) SAVLIB(SPOR40) DEV(OPT01) VOL(BDS) RSTLIB(QTEMP)  
OPTFILE(SPOR40)
```

If you are using Save files:

You should have a save file containing your media. Verify the contents and note the library saved:

```
DSPSAVF FILE(mylib/myfile)
```

The save file should contain objects for library **SPOR40**.

Restore the update objects from the save file containing library **SPOR40** into library QTEMP:

```
RSTOBJ OBJ(BSOUP*) SAVLIB(SPOR40) DEV(*SAVF) SAVF(mylib/myfile) RSTLIB(QTEMP)
```

5. Execute the update procedure. Enter one of the following:

Note: If you are planning to install library **BDSBASE** into an ASP other than the system ASP (ASP 1), refer to Appendix K, “ASP Considerations” to determine the values for the BASASP parameter on the following BSOUPD command. Refer to the command help text for more information regarding the BASASP parameter.

Note: If you have installed Spool Organizer’s program or data libraries into an IASP, verify that the IASP device’s status is **AVAILABLE**. Use the command WRKCFGSTS CFGTYPE(*DEV) CFGD(your-IASP-dev).

If you are using Tape or CD-ROM (Press F4 to prompt):

```
QTEMP/BSOUPD DEV(XXXXX)
```

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

If you are using a Save file (Press F4 to prompt):

QTEMP/BSOUPD DEV(*SAVF) PGMSAVF(mylib/myfile)

Enter the save file containing library **SPOR40** for mylib/myfile.

6. Spool Organizer is now updated to the new release. You will receive a message that your update has completed.

7. Move product libraries to other ASPs (optional). After all instances of all Broderick Data System products installed in this LPAR have updated to ASP-compatible releases, you can move the BDS product libraries to other ASPs if desired. Refer to Appendix K, "ASP Considerations" for more information.

8. Access the BDS Software Server (optional).

Note: Your AS/400 must be connected to the Internet to perform this procedure.

a) If you have not done so previously, access the tailoring options screen:

BRODERICK/BSOSETUP

b) Note the fields "BDS Access Userid" and "Password". You will need a user ID and password to access some of the server options. If needed, contact BDS administration to get this information. If you add your user id and password, press **ENTER** to enter them and re-enter the setup command.

c) Press F14, E-Comm. The Software Server display will appear. Take note of the options available to you. When you are finished, press F3 to exit.

Submit Update to Batch

Broderick Data Systems recommends the update procedure be performed interactively at a workstation. However, the update can be submitted to batch if necessary. To do this, a simple CL program must be written. This CL program must contain the commands that would be entered interactively. See above for your exact commands and format. An example procedure follows:

1) Restore the command BSOUPD from the media (CD, save file) into library QTEMP. It will be needed to compile your CL program.

2) Create a source code for a CL program. The program must contain the restore command (RSTOBJ) and the update command (BSOUPD). You may add other commands such as backup or stop commands. For example:

PGM

SPOOLORGANIZER/400™

UPDATE INSTRUCTIONS

```
RSTOBJ OBJ(BSOUP*) SAVLIB(SPOR40) DEV(*SAVF) SAVF(MYLIB/SPOR40) RSTLIB(QTEMP)
QTEMP/BSOUPD DEV(*SAVF) PGMSAVF(MYLIB/SPOR40) DTASAVF(MYLIB/SPOR40D)
ENDPGM
```

- 3) Interactively compile the program (CRTPGM) to your library.
- 4) Delete command BSOUPD from QTEMP.
- 5) Perform all activities specified in the above update instructions that need to be done before running the program, and are not in the program. (Sign on as QSECOFR, backup, stop all, etc.)
- 6) Submit a job to batch that calls the program you created. Wait for it to end. Look over the job log created by the update procedure. There should be a message “Spool Organizer Release XXX now installed” at the end of the log.
- 7) Perform all activities specified in the above update instructions that need to be done after running the program, and are not in the program. (Restart Monitors, etc.)