

APPENDIX A: ELECTRONIC MEDIA DISTRIBUTION

The user can distribute Spool PDF Overlay/400 to remote systems electronically. Thus the user can install or update E-mail Utilities on similar remote systems (i.e. AS/400 to AS/400's). A working **APPC/APPN** or **TCP** link to the remote system, and a file transfer program such as **FileXfer3X/400** or **FTP** is needed to do this. Below are the steps you must perform to transmit Spool PDF Overlay/400 to remote systems. **Please note** that a thorough knowledge of the operating systems involved is suggested.

The **AS/400** media consists of **2** libraries:

SPDF40
SPDF40DATA

The steps to distribute Spool PDF Overlay/400 are:

Source System

- 1) Restore libraries **SPDF40** and **SPDF40DATA** from the **BDS**. Media. For optical disk, the libraries are contained in optical files **SPDF40** and **SPDF40D**.

Note: You must be signed on as a user with ***SECADM** authority when performing the restores.

- 2) Create two save files **SAVSPDF** and **SAVSPDFD**.
- 3) Save library **SPDF40** into save file **SAV SPDF**, and library **SPDF40DATA** into save file **SAVSPDFD**.
- 4) Delete the libraries **SPDF40** and **SPDF40DATA**.
- 5) Transmit the save files to the remote system(s).

Remote System(s)

- 1) Create and receive the transmitted save files, if necessary.
- 2) Proceed with the update or install instructions with the following:

When requested to restore the install or update objects into library **QTEMP**, use the save file option. Enter save files **SAVSPDF** and **SAVSPDFD**.

When executing the install or update command (**BOVINS** or **BOVUPD**) use the save file option. Enter save files **SAVSPDF** and **SAVSPDFD**.

Spool PDF Overlay/400 will be installed or updated.