

Release Compatibility Table

This chapter describes the procedures to determine if the new release of FileXfer3X/400 is compatible with existing instances of BDS software that are installed on this LPAR. To determine the existing software's release, run the corresponding command for each/all instances of BDS software installed on this LPAR.

<u>Product</u>	<u>Command</u>
Spool Organizer/400	BRODERICK/BSOSETUP
Remote SpoolPrint/400	BRODERICK/BRSPSETUP
FileXfer/400	BRODERICK/BXFERSETUP
E-mail Utilities/400	BRODERICK/BEMSETUP
Spool PDF Overlay/400	BRODERICK/BOVSETUP

Note: If needed, set the ASP Group to the proper value (**SETASPGRP**) if needed before running the above commands.

The following table shows the other products' oldest release that is compatible with the new release of FileXfer3X/400/400:

<u>Product</u>	<u>Release</u>
Spool Organizer/400	5.7 0000
Remote SpoolPrint/400	6.2 0000
FileXfer/400	5.2 0000
E-mail Utilities/400	1.0 0000
Spool PDF Overlay/400	1.0 0000

Any installed BDS instance with a release that is earlier than the above values is not compatible with the new release and must be updated at the same time this FileXfer3X/400 instance is updated. Failure to update non-compatible BDS software instances could cause other BDS software to stop working after this FileXfer3X/400 install/update is performed.

You can update the BDS software instances in any order.

For example, if the **BRODERICK/BSOSETUP** command shows that Spool Organizer 5.6 1701 is installed on this LPAR, it must be updated along with updating FileXfer3X/400.

FILEXFER3X/400™