

APPENDIX C: ELECTRONIC MEDIA DISTRIBUTION

The user can distribute Credit Card/400 to remote systems electronically. Thus the user can install or update Credit Card/400 on other remote systems. A working **APPC/APPN** or **TCP** link to the remote system, and a file transfer program such as **FileXfer3X/400**, **E-mail Utilities** or **FTP** is needed to do this. Below are the steps you must perform to transmit Credit Card/400 to remote systems. **Please note** that a thorough knowledge of the operating systems involved is suggested.

The **AS/400** media consists of **2** libraries:

CCRD40
CCRD40DATA

The steps to distribute Credit Card/400 are:

Source System

- 1) Restore libraries **CCRD40** and **CCRD40DATA** from the **BDS**. Media. For optical disk, the libraries are contained in optical files **CCRD40** and **CCRD40D**.

Note: You must be signed on as a user with ***SECADM** authority when performing the restores.

- 2) Create two save files **SAVCCRD** and **SAVCCRDD**.
- 3) Save library **CCRD40** into save file **SAVCCRD**, and library **CCRD40DATA** into save file **SAVCCRDD**.
- 4) Delete the libraries **CCRD40** and **CCRD40DATA**.
- 5) Transmit the save files to the remote system(s).

Remote System(s)

- 1) Create and receive the transmitted save files, if necessary.
- 2) Proceed with the update or install instructions with the following:

When requested to restore the install or update objects into library **QTEMP**, use the save file option. Enter save files **SAVCCRD** and **SAVCCRDD**.

When executing the install or update command (**BCCINS** or **BCCUPD**) use the save file option. Enter save files **SAVCCRD** and **SAVCCRDD**.

Credit Card/400 will be installed or updated.